

IN THE CLAIMS

Please amend the claims as follows:

1. (currently amended) A communications system, comprising:
 - a transmission unit ~~100~~ comprising:
 - a noise source ~~110~~ for generating a noise signal;
 - a signal generator ~~120~~ connected to the noise source ~~generator 110~~ and generating a colored noise-like preamble from at least the noise signal;
 - a modulator ~~130~~ connected to the signal generator ~~120~~ for modulating the colored noise-like preamble;
 - a switching device ~~150~~ having at least a first input ~~152~~, a second input ~~154~~ and an output ~~156~~, the first input ~~152~~ being connected to the modulator ~~130~~;
 - an ISM spread spectrum modulator ~~160~~ connected to the second input ~~154~~ of the switching device ~~150~~ and providing an ISM transmission signal; and
 - a transmitter ~~170~~ connected to the output of the switching device ~~156~~ wherein when the switching device ~~150~~ is in a first position the colored noise-like preamble is provided as a transmitter output signal and when the switching device ~~150~~ is in a second position the ISM transmission signal is provided as the transmitter output signal wherein the colored noise-like preamble is transmitted by the transmitter before the ISM transmission signal;
 - a receiving unit ~~500~~ comprising:
 - an antenna ~~510~~ for receiving the transmitter output signal transmitted by the transmission unit ~~100~~, the antenna ~~510~~ adjusting an antenna pattern for improving reception of the transmitter output signal by the transmission unit ~~100~~;
 - a signal processor ~~515~~ connected to the antenna ~~510~~, the antenna ~~510~~ producing an antenna output signal including the antenna pattern and the transmitter output signal, the signal processor ~~570~~ evaluating the antenna output signal and determining at least the presence of the colored noise-like preamble in the antenna output signal.

2. (currently amended) The communications system of Claim 1, wherein the signal processor ~~515~~ comprises:

a downconverter ~~520~~ connected to the antenna ~~510~~ for downconverting the antenna output signal;

an ISM receiver ~~540~~ connected to the downconverter ~~520~~ for receiving the antenna output signal and receiving the ISM transmission signal when the ISM transmission signal is present in the antenna output signal;

a sampler ~~550~~ connected to the downconverter ~~520~~ for sampling the antenna output signal;

a one-bit quantizer ~~560~~ connected to the sampler ~~550~~ for quantizing the antenna output signal into one-bit segments; and

an arc-sine law processor ~~570~~ connected to the one-bit quantizer ~~560~~ and antenna ~~510~~ for determining the presence of the colored noise-like preamble in the antenna output signal and the arc-sine law processor ~~570~~ instructing the antenna ~~510~~ to at least cause movement of the antenna pattern.

3. (currently amended) The communications system of Claim 2, wherein the receiving unit ~~500~~ further comprises a capacitor ~~530~~ connected between the downconverter ~~520~~ and the sampler ~~550~~ for removing any DC levels in the antenna output signal.

4. (currently amended) The communications system of Claim 1, wherein the noise source ~~110~~ comprises a broadband noise source.

5. (currently amended) The communications system of Claim 1, wherein the transmitting unit ~~100~~ further comprises an antenna ~~180~~ connected to the transmitter ~~170~~ wherein the transmitter ~~170~~ drives the antenna ~~180~~ with the output signal.

6. (currently amended) The communications system of Claim 1, wherein the antenna 510 comprises a plurality of antennas 610, 620 for receiving the transmitter output signal transmitted by the transmission unit 400 and the receiving unit 500 further comprising an ISM receiver 540 connected to the signal processor for receiving the antenna output signal and receiving the ISM transmission signal when the ISM transmission signal is present in the antenna output signal.

7. (currently amended) The communications system of Claim 6, wherein the antenna output signal comprises a sum beam 710 and a difference beam 730, the signal processor 515 receiving the sum beam 710 and the difference beam 730 and the signal processor 515 comprising:

- a first delay unit 712 connected to the plurality of antennas 610, 620 and receiving the sum beam 710, the first delay unit 712 delaying the sum beam 710;

- a first complex conjugator 714 connected to the first delay unit 712 for conjugating the sum beam 710 and providing a first conjugator output signal;

- a first multiplier 716 connected to the first complex conjugator 714 and receiving the sum beam 710, the first multiplier 716 multiplying the sum beam 710 with the first conjugator output signal to produce a first multiplier output signal;

- an first integrator 720 connected to the first multiplier 716 and integrating the first multiplier output signal and providing a first integrator output signal;

- a monopulse producing module 750 connected to the first integrator 720;

- a second delay unit 732 connected to the plurality of antennas 610, 620 and receiving the difference beam 730, the second delay unit 732 delaying the difference beam 730;

- a second complex conjugator 734 connected to the second delay unit 732 for conjugating the difference beam 730 and providing a second conjugator output signal;

- a second multiplier 736 connected to the second complex conjugator 734 and receiving the sum beam 710, the second multiplier 736 multiplying the sum beam 710

with the second complex conjugator output signal to produce a second multiplier output signal; and

a second integrator ~~740~~ connected to the second multiplier ~~736~~ and the monopulse producing module ~~750~~, the second integrator ~~740~~ integrating the second multiplier output signal and providing a second integrator output signal wherein the monopulse producing module ~~750~~ calculates an angle of arrival from the first integrator output signal and the second integrator output signal.

8. (currently amended) A system for short range communications, comprising:

a transmitter ~~170~~ capable of transmitting a colored noise-like preamble;

a receiver ~~540~~ for receiving the colored noise-like preamble and including an antenna ~~510~~ with an antenna pattern, a direction of the antenna ~~510~~ being controllable by the receiver ~~540~~; and

a signal processor ~~515~~ connected and responsive to the receiver ~~540~~ for detecting and estimating the strength of the colored noise-like preamble.

9. (currently amended) The system of Claim 8, wherein the antenna pattern comprises a spatial null adapted to be oriented electronically.

10. (currently amended) The system of Claim 8, wherein the signal processor is adapted to implement an arc sine law.

11. (currently amended) The system of Claim 8, wherein the colored noise-like preamble is composed of interleaved sequences of samples of colored noise.

12. (currently amended) The system of Claim 8, wherein the transmitter ~~170~~ comprises an ISM transmitter.

13. (currently amended) The system of Claim 8, wherein the receiver 540 comprises an ISM receiver.

14. (currently amended) A system for short range communications, comprising:

- a transmitter ~~170~~ capable of transmitting a colored noise-like preamble;
- a receiver 540 for receiving the colored noise-like preamble and including at least two antennas ~~610, 620~~ having at least two output signals, wherein each of the two output signals are independently provided; and
- a signal processor ~~515~~ connected to the receiver 540 and combining the at least two antenna output signals.

15. (currently amended) The system of Claim 14, wherein the signal processor ~~515~~ combines the at least two antenna output signals to mitigate an interference signal.

16. (currently amended) The system of Claim 14, wherein the signal processor ~~515~~ combines the at least two antenna output signals to enhance reception of the colored noise-like preamble.

17. (currently amended) The system of Claim 14, wherein the transmitter ~~170~~ comprises an ISM transmitter.

18. (currently amended) The system of Claim 14, wherein the receiver 540 comprises an ISM receiver.

19. (new) A system for short range communications, comprising:
a transmitter capable of transmitting a colored noise-like preamble;
a receiver for receiving the colored noise-like preamble and including at least one antenna with an antenna pattern, a direction of the antenna being controllable by the receiver; and
a signal processor connected and responsive to the receiver for detecting and estimating the strength of the colored noise-like preamble, and for causing reorientation of the antenna pattern of the at least one antenna based upon the preamble strength.
20. (new) The system of Claim 19, wherein the antenna pattern comprises a spatial null adapted to be oriented electronically based upon the preamble strength.